

Model	HM-1000			HM-1200			HM-1500		
<b>Input Data (DC)</b>									
Commonly used module power (W)	200~310			240~380			300~470		
Module compatibility	60-cell or 72-cell PV modules			60-cell or 72-cell PV modules			60-cell or 72-cell PV modules		
Peak power MPPT voltage range (V)	27~48			29-48			36~48		
Start-up voltage (V)	22			22			22		
Operating voltage range (V)	16~60			16-60			16~60		
Maximum input voltage (V)	60			60			60		
Maximum input current (A)	4*10.5			4*11.5			4*11.5		
<b>Output Data (AC)</b>									
Rated output power (VA)	1000			1200			1500		
Rated output current(A)	4.55	4.35	4.17	5.45	5.22	5	6.82	6.52	6.25
Nominal output voltage/range (V)	220/180-275 <sup>1</sup>	230/180-275 <sup>1</sup>	240/180-275 <sup>1</sup>	220/180-275 <sup>1</sup>	230/180-275 <sup>1</sup>	240/180-275 <sup>1</sup>	220/180-275 <sup>1</sup>	230/180-275 <sup>1</sup>	240/180-275 <sup>1</sup>
Nominal frequency/range (V)	50/45-55 <sup>1</sup> or 60/55-65 <sup>1</sup>			50/45-55 <sup>1</sup> or 60/55-65 <sup>1</sup>			50/45-55 <sup>1</sup> or 60/55-65 <sup>1</sup>		
Power factor (adjustable)	>0.99 default 0.8 leading...0.8 lagging			>0.99 default 0.8 leading...0.8 lagging			>0.99 default 0.8 leading...0.8 lagging		
Total harmonic distortion	<3%			<3%			<3%		
Maximum units per branch <sup>2</sup>	5	5	5	4	4	4	3	3	3
<b>Efficiency</b>									
CEC peak efficiency	96.70%			96.70%			96.70%		
CEC weighted efficiency	96.50%			96.50%			96.50%		
Nominal MPPT efficiency	99.80%			99.80%			99.80%		
Nighttime power consumption (mW)	<50			<50			<50		
<b>Mechanical Data</b>									
Ambient temperature range (°C)	-40~+65								
Dimensions (W×H×D mm)	280 x 176 x 33								
Weight (kG)	3.75								
Enclosure rating	Outdoor-NEMA (IP67)								
Cooling	Natural convection – No fans								
<b>Features</b>									
Communication	2.4GHz Proprietary RF(Nordic)								
Monitoring	Hoymiles Monitoring System								
Compliance	VDE-R-N 4105: 2018, EN 50549-1: 2019, VFR 2019, IEC/EN 62109-1/-2, IEC/EN 61000-6-1/-2/-3/-4, IEC/EN 61000-3-2/-3								

\*1 Nominal voltage/frequency range can be changed due to the requirements of local power department.

\*2 Refer to local requirements for exact number of microinverters per branch.

### High Reliability Based on World's Top Supplier Partners








