

## TRIPLE POWER

- Safest LiFePO<sub>4</sub> battery
- 90% DOD
- Cycle life>6000 times
- IP65 protection level
- Floor or wall mounting
- Less self consumption
- Quick installation
- No toxic heavy metals or caustic materials



V1

V2

**TRIPLE**  
POWER

Global: +86 571-56260011

Email: [info@triple-power.com](mailto:info@triple-power.com)

# T-BAT SYS-HV Configuration List

	T-BAT H 5.8	T-BAT H 11.5	T-BAT H 17.3	T-BAT H 23
Nominal Voltage [V]	115.2	230.4	345.6	460.8
Operating Voltage [V]	100-131	200-262	300-393	400-524
Battery Type	Li-ion (LFP)	Li-ion (LFP)	Li-ion (LFP)	Li-ion (LFP)
Total Capacity [kWh]	5.8	11.5	17.3	23.0
Usable Capacity <sup>[1]</sup> [kWh]	5.1	10.4	15.5	20.7
Faradic Charge Efficiency [%]	99	99	99	99
Battery Roundtrip Efficiency [%]	95	95	95	95
Standard Power [kW]	2.8	5.7	8.6	11.5
Max Power [kW]	4.0	8.0	12.0	16.1
Recommend Charge/Discharge Current [A]	25	25	25	25
Max Charge/Discharge Current [A]	35	35	35	35
Short Circuit Current[A]	760	760	760	760
Cycle Life	>6000 Cycles	>6000 Cycles	>6000 Cycles	>6000 Cycles
Warranty [Year]	10	10	10	10

Available Operating Temperature Range [°C]	0 to 55
Full-load Operating Temperature Range [°C]	5 to 48
Relative Humidity [%]	4 to 100 (condensing)
Altitude [m]	Below 2000
Protection	IP65

System to Inverter	CAN2.0
Battery to Battery/BMS	RS485
Data Collection Port /FW UPDATE	CAN2.0
Master Control Working Mode Indicator	1 LED
Master Control Capacity Indicator	4LED (25%, 50%, 75%, 100%)
Battery Module LED	2 LED
Reset	Button
Switch ON/OFF	Buttonx1 + breakerx1

Safety	CE, RCM, IEC62619, UL1973, ROHS, REACH
UN Number	UN3840
Hazardous Materials Classification	Class 9
Transport Testing Requirement	UN38.3

Dimensions(LxWxH) [mm]	474x193x708	474x193x708+474x193x647	474x193x708+(474x193x647)x2	474x193x708+(474x193x647)x3
Weight [kg]	72.2	72.2+68.5	72.2+68.5x2	72.2+68.5x3

[1] Test conditions:90% DOD, 0.2C charger & discharger @+25°C

\* X3 Hybrid inverter can connect 2-4pcs of T58 batteries(1pc of T58 master, and rest 1-3pcs of T58 slave).

\* X1 Hybrid inverter can connect 1-3pcs of T58 batteries(1pc of T58 master, without T58 slave, or with 1-2pcs of T58 slave).

\* With BMS Parallel Box-II, the maximum battery quantity connected on each inverter varies, please kindly check datasheet of BMS Parallel Box-II.

\* Maximum Charge/Discharge Current may be variant with different inverter models

V2.2\*Information may be subject to change without notice. 650.00012.00